

ProMax LB06 Multifunction Process Calibrator is an advanced high-precision multifunction process calibrator, you can easily source and measure almost any process parameter and process device sensors, it also includes Hart, Modbus Master, and slave, process controlling signal generator calibrator, digital multimeter function all in one. This is an upgraded premium version of the LB02 process calibrator.

Measure and source mA, volts, temperature (RTDs and thermocouples), frequency, and ohms.

Whether you're calibrating instruments, troubleshooting a problem, or running routine maintenance, ProMax LB06 process calibrators can help you get the job done faster. It does so many different tasks, so quickly and so well, it's the only process calibrator you need to carry

ProMax LB06 can generate the following signals -

- DC Voltages from 0 to 11V & DC Mini Voltages from 0 to 110mV
- Current Signals from 0 to 24mA
- Resistance from 0 to 2200 ohms
- Frequency 0 to 10Hz
- Thermocouple Simulation Signal
- RTD like PT100, PT1000, Cus50
- 24V Fixed Voltage for Testing

ProMax LB06 is ready to perform as a powerful, yet easy-to-use field calibrator. Its simple controls, with menus, make operation easy and the backlit display provides better visibility in poor light. It features a small, streamlined shape and a rugged, reliable design that makes it ideal for standing up to harsh field conditions.



Applications

- **Multifunctional Sensor Calibrator:** Calibrate temperature, pressure, voltage, current, resistance, and frequency. Since it both measures and sources, you can troubleshoot and calibrate all with one rugged tool
- **Multifunctional Sensor Simulator:** Simulate multiple sensors for troubleshooting and debugging systems. Engineers can use this calibrator to identify the faults in the sensor, controller, or wiring by simulating sensor output signals and carrying out test procedures.
- **Process Automation:** Communicate MODBUS Master, MODBUS Slave, and Hart communicator/operator function.
- **Hand-Held Operation.** Small enough to fit easily into a tool bag and to use in tight spaces. Runs an entire shift on a rechargeable Li-ion battery pack. Great for testing on the field.
- **2 operating modes:** Measure & Source (generate) —enable technicians to troubleshoot, calibrate, or maintain instrumentation with just one tool.
- The signal calibrator can output a user-defined signal when a user enters a signal value through digit buttons.
- Simulation and measurement of thermocouples and temperature sensors like PT100, PT1000, CU50.. etc.
- Debugging of industrial field PLCs
- Process Instrumentation: Signal Generators, Signal measurement, Valve Adjustment, Inverter control
- PLC & Control Panel debugging by bypassing sensors and sensor calibrations
- LED & Equipment Testing or Control

Versatile Troubleshooting Tool

Engineers can power Sensor Transmitters under test using the inbuilt 24V loop supply with simultaneous mA measurement so you can test a transmitter out of the circuit and better isolate problems.

Source mA with simultaneous pressure measurement to conduct valve and I/P (Input current/Output pressure) tests in a single device. You can also test flow meters with frequency and CPM (counts per minute) functions and perform fast linearity tests with auto-step and auto-ramp features so you can quickly verify the mA signal at different output levels.

It can output and measure 4 to 20mA Current, Voltage, Frequency Pulses, Thermocouple, and RTD Sensor. It is widely used as an mV mA calibrator, temperature calibrator, frequency signal calibrator, 4-20mA loop calibrator, multimeter, etc. It supports full-function operating mode and user-defined output settings.

Can be used in process and instrumentation systems like automation and industrial applications through MODBUS Master, MODBUS Slave, and Hart communicator/operator functions.

Features

- High accuracy of 0.025% +1/2 digits; widely used as frequency calibrator, mA mV loop calibrator, temperature calibrator, etc.
- Have a full-function operating mode, the user can enter any value through digits buttons, and the calibrator outputs a signal directly
- Standard MODBUS Master, MODBUS Slave, Hart communicator/operator function.
- Signal output simulation and measurement: 0-10KHz frequency, 4-20mA source or passive signal, 0-11V, 0-110mV, 20-400Ω, standard R, E, S, K, J, B, T, N type thermocouple, PT100, CU50, 24V outputs, etc.
- Offers easy and convenient handheld operation. 2200mAH rechargeable battery inside has a battery status indicator, very suitable and convenient to use indoors or outdoors in industrial sites.
- High-resolution color LCD, has a backlight for different lighting conditions, large screen clear display
- Can be used as a signal generator, frequency calibrator, and multifunction process calibrator.
- Have description in Hz, V, mV, mA, RTD, TC, Step, and Ω keys, which enables the user to operate it easily
- Internal polarity Reverse connection and Over current protection; Protection voltage 30V

Technical Specifications

Output Parameters

FUNC	OUT UNIT	RANGE	SET STEP	ACCURACY (SP: setting point)	
DC. V	V	0~11.00V	0.01/0.1/1	±0.025%SP ±0.004V	
DC. mV	mV	0~110.00mV	0.1/1/10	±0.025%SP ±0.02mV	
DC. mA	Sink/Source/Program	0~24.00mA	0.01/0.1/1/4	±0.025%SP ±0.004mA	
Ohm	Ω	0~400Ω	1/10/0100	±0.025%SP ±0.3Ω	
		400~2200Ω	1/10/0100	±0.05%SP ±1.5Ω	
Frequency	KHz	0-10	0.01/0.1/1	±0.05%SP ±2Hz	
TC	R	0~1700°C	1/10/0100		
	S	0~1600°C			
	B	500~1800°C		±0.1%SP ±3°C	
	K	-200~1370°C			±0.05%SP ±0.5°C (K)
					±0.05%SP ±0.3°C (E)
					±0.05%SP ±0.4°C (J)

	E	-200~1000°C		±0.05%SP ±0.5°C(T)
	J	-200~1200°C		
	T	-200~400°C		
	N	-200~1300°C		
RTD	PT1000	-50~300°C	1/10/0100	±0.1%SP ±0.5°C
	Pt100	-200~850°C		±0.1%SP ±0.8°C
	Cu50	-50~150°C		±0.1%SP ±1.5°C
24V	24V	24V: Cannot be set. Current measurement:0~24.000 mA	NONE	
	mA			

Measurement Parameters

FUNC	UNIT	RANGE	RESOLUTION	ACCURACY (RD: Read number)
DC.V	V	-30~30.000V	0.001V	±0.025%RD ±0.004V
DC. mV	mV	-150~150.00mV	0.01mV	±0.025%RD ±0.02mV
DC. mA	mA	-30~30.000mA	0.001mA	±0.025%RD ±0.004mA
Ohm	Ω	0~999.9Ω	0.1Ω	±0.025%RD ±0.2Ω
		1000-2500	1Ω	±0.025%RD ±1Ω
Frequency	KHz	0-10	0.001	±0.05%RD ±2Hz
TC	R	0~1700°C	0.1°C	±0.1%RD ±3°C (R,S,B)
	S	0~1600°C		
	B	500~1800°C		
	K	-200~1370°C		±0.025%RD ±0.5°C (K) ±0.025%RD ±0.3°C (E) ±0.025%RD ±0.4°C (J) ±0.05%RD ±0.5°C(T) ±0.025%RD ±0.8°C (N)
	E	-200~1000°C		
	J	-200~1200°C		
	T	-200~400°C		
N	-200~1300°C			
RTD	Pt1000	-50~300°C	0.1°C	±0.1%RD ±0.5°C
	Pt100	-200~850°C		±0.1%RD ±0.8°C
	Cu50	-50~150°C		±0.1%RD ±1.5°C
Range switch	mA	0~9990 engineering unit (for current measurement and measure the current of 24V output)	related to engine	

Terms and Conditions Agreement

Read and understand this catalogue.

Please read and understand this catalogue before purchasing the products. Please consult your ProMax sales/technical representative if you have any questions or comments.

Warranties.

(a) Warranty. ProMax does not offer any warranty/guarantee/replacement/returns for products once sold. Since these products are used in research/testing/production with other components, it is beyond our scope to determine the working of our product in your application. ProMax disclaims all other warranties, express or implied.

(b) Limitations. ProMax MAKES NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, ABOUT NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE OF THE PRODUCTS. THE BUYER ACKNOWLEDGES THAT IT ALONE HAS DETERMINED THAT THE PRODUCTS WILL SUITABLY MEET THE REQUIREMENTS OF THEIR INTENDED USE.

ProMax further disclaims all warranties and responsibility of any type for claims or expenses based on infringement by the Products or otherwise of any intellectual property right.

(c) Buyer Remedy. ProMax sole obligation hereunder shall be, at ProMax's election, to (i) replace (in the form originally shipped with Buyer responsible for labor charges for removal or replacement thereof) the non-complying Product, (ii) repair the non-complying Product, or (iii) repay or credit Buyer an amount equal to the purchase price of the non-complying Product; provided that in no event shall ProMax be responsible for warranty, repair, indemnity or any other claims or expenses regarding the Products unless ProMax analysis confirms that the Products were properly handled, stored, installed and maintained and not subject to contamination, abuse, misuse or inappropriate modification or any other reason. Return of any Products by Buyer must be approved in writing by ProMax before shipment. ProMax Companies shall not be liable for the suitability or unsuitability or the results from the use of Products in combination with any electrical or electronic components, circuits, system assemblies or any other materials or substances or environments. Any advice, recommendations or information is given orally or in writing, are not to be construed as an amendment or addition to the above warranty. See <http://www.probots.co.in/> or contact your ProMax representative for published information.

Limitation on Liability; Etc.

ProMax COMPANIES SHALL NOT BE LIABLE FOR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, LOSS OF PROFITS OR PRODUCTION OR COMMERCIAL LOSS IN ANY WAY CONNECTED WITH THE PRODUCTS, WHETHER SUCH CLAIM IS BASED IN CONTRACT, WARRANTY, NEGLIGENCE OR STRICT LIABILITY.

Further, in no event shall liability of ProMax Companies exceed the individual price of the Product on which liability is asserted.

Suitability of Use. ProMax Companies shall not be responsible for conformity with any standards, codes or regulations which apply to the combination of the Product in the Buyer's application or use of the Product. At Buyer's request, ProMax will provide applicable third party certification documents identifying ratings and limitations of use which apply to the Product. This information by itself is not sufficient for a complete determination of the suitability of the Product in combination with the end product, machine, system, or other application or use. Buyer shall be solely responsible for determining appropriateness of the particular Product with respect to Buyer's application, product or system. Buyer shall take application responsibility in all cases.

NEVER USE THE PRODUCT FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY OR IN LARGE QUANTITIES WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISKS, AND THAT THE ProMax PRODUCT(S) IS PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

Programmable Products.

ProMax Companies shall not be responsible for the user's programming of a programmable Product, or any consequence thereof. Performance Data.

Data presented in ProMax Company websites, catalogs and other materials is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of ProMax's test conditions, and the user must correlate it to actual application requirements. Actual performance is subject to the ProMax's Warranty and Limitations of Liability.

Change in Specifications.

Product specifications and accessories may be changed at any time based on improvements and other reasons. It is our practice to change part numbers when published ratings or features are changed, or when significant construction changes are made.

However, some specifications of the Product may be changed without any notice. When in doubt, special part numbers may be assigned to fix or establish key specifications for your application. Please consult with your ProMax's representative at any time to confirm actual specifications of purchased Product. Errors and Omissions. Information presented by ProMax Companies has been checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical or proofreading errors or omissions.